



T60TX-03STL



T60TX-06STL



T60TX-08STL

Midi-T Transmitter T60TX-0xSTL:	
Application areas:	Doors, entrances, gates, winches, pumps, crushers, lighting, conveyor belts, hydraulics a.o.
Frequency:	433,92 MHz
Mod. Type:	FSK
Coding:	Digital pulse code
Code comb.:	Adjustable codes; 59.049 (System 460: 6.561) Unique codes; 16.777.216
Functions:	1, 2, 3, 4, 6 or 8
Output:	7 mW (by 50 ohm)
Antenna:	Built-in
Power supply:	3 Exchangeable 1,5V batteries type:AAA (battery change once a year with normal use)
Power consumption:	Apr. 20 mA
Temperature:	-20° C to +55° C
Weight:	Apr. 120 g incl. battery
Dimensions:	113 x 66 x 35 mm (with clip)
Protection:	IP 65
Recommended receiver:	Standard receiver with 1,3, 4, 6 or 8 relays, DIN and plug-in receiver (fully compatible with system 460).

TELE RADIO AB

Sweden, Main office
Tel. +46 (0)31-724 54 60
e-mail: info@tele-radio.com

www.tele-radio.com

TELE RADIO SVERIGE

Sweden
Tel. +46 (0)31-724 98 00
e-mail: sverige@tele-radio.com

TELE RADIO OÜ

Estonia
Tel. +372 44 511 55
e-mail: m.jyrissoo@tele-radio.com

TELE RADIO GmbH

Germany
Tel. +49 (0)94 51-944 8 550
e-mail: kontakt@tele-radio-gmbh.de

TELE RADIO ASIA

China
Tel. +86-(0)592-3111168
e-mail: b.sun@tele-radio.cn

TELE RADIO TURKEY

Turkey
Tel. +90-532 292 4448
e-mail: c.melevioglu@tele-radio.com

TELE RADIO LTD

England
Tel. +44 (0) 1625 509125
e-mail: sales@teleradiouk.com

TELE RADIO LLC

North America & Latin America
Tel. +1 (305) 459 0763
e-mail: america@tele-radio.com

TELE RADIO BV

Benelux
Tel. +31-(0)70-419 41 20
e-mail: info@teleradio.nl

TELE RADIO AS

Norway
Tel. +47-6933 4900
e-mail: norway@tele-radio.com